

# WHITE BALANCE CONTROL AMOUNT CALCULATING DEVICE

## BACKGROUND OF THE INVENTION

### 1. Field of the Invention

5           The present invention relates to an electronic still camera by which an image signal obtained by an imaging device is recorded, and especially, to a device which calculates a white balance control amount for adjusting a color of a color image obtained based on the image signal.

### 10   2. Description of the Related Art

          Conventionally, for calculating a white balance control amount, there is known a device in which only pixel signals of achromatic color are extracted from all of the pixel signals forming a single image, and the white balance control amount  
15 is calculated based on the pixel signals of achromatic color. Namely, in the pixel signals of the achromatic color, pixels other than the subject image, which the photographer intends to photograph, are contained. On the other hand, there is known another device, in which a white balance control amount  
20 is calculated using all of the pixel signals forming the single image. In the latter device, similarly to the former device, pixels other than the subject image, which the photographer intends to photograph, are contained.

          When a tint of an image portion of the subject to be  
25 photographed and that of an image portion other than the

subject are close to each other, the white balance control amount would be proper even though pixel signals included the portion other than the subject. Conversely, when tint is drastically locally varied in the image, the white balance  
5 adjustment may not be performed properly for the subject to be photographed.

#### SUMMARY OF THE INVENTION

Therefore, an object of the present invention is to provide a white balance control amount calculating device by  
10 which a white balance adjustment can be always properly performed regardless of the tint of the image as a whole.

According to the present invention, there is provided a white balance control amount calculating device comprising an image signal generating processor, an image area extracting  
15 processor and a control amount calculating processor.

The image signal generating processor generates an image signal corresponding to a first image formed on a light receiving surface of an imaging device. The image area extracting processor extracts at least one image area, which  
20 contains a second image of a subject positioned at a predetermined distance from an electronic still camera, from the first image. The control amount calculating processor calculates a control amount for performing a white balance adjustment, based on the image signal relating to the at least  
25 one image area.

Further, according to the present invention, there is provided a device for calculating a white balance control amount for an electronic still camera which photographs an image containing at least one subject and at least one portion  
5 other than the subject, the white balance control amount calculating device comprising an imaging device, an image area extracting processor and a control amount calculating processor.

The imaging device generates an image signal  
10 corresponding to the image. The image area extracting processor extracts at least one image area, each containing one of the aforementioned at least one subject, from the image. The control amount calculating processor calculates a control amount for performing a white balance adjustment,  
15 based on the image signal relating to the image area.

#### BRIEF DESCRIPTION OF THE DRAWINGS

The objects and advantages of the present invention will be better understood from the following description, with reference to the accompanying drawings in which:

20 Fig. 1 is a block diagram showing an electronic still camera provided with a white balance control amount calculating device of a first embodiment of the present invention;

Fig. 2 is a block diagram showing a construction of a  
25 light beam projection unit;

Fig. 3 is a perspective view showing an interchangeable lens and a focusing ring mounted in the interchangeable lens, in which the interchangeable lens and the focusing ring are disassembled;

5        Fig. 4 is a view showing an example of an image observed through a view-finder;

Fig. 5 is a view showing a principle behind a distance measurement;

10       Fig. 6 is a timing chart showing a distance measurement light beam, a reflected light beam, a gate pulse and a distribution of an amount of a light beam received by a CCD;

Fig. 7 is a plan view showing a disposition of photodiodes and a vertical transfer unit, which are provided in the CCD;

15       Fig. 8 is a sectioned elevational view of the CCD;

Fig. 9 is timing chart of a distance information sensing operation by which data, corresponding to a distance from an electronic still camera to each point on a surface of the measurement subject, is sensed;

20       Figs. 10A and 10B show a flowchart of a white balance adjustment routine of the first embodiment;

Figs. 11A and 11B show a flowchart of a white balance adjustment routine of a second embodiment; and

25       Fig. 12 is a histogram, in which a reciprocal number of a distance "d" from the electronic still camera to the

subject is defined as the axis of abscissas and a number of pixels corresponding to the distance is defined as the axis of ordinates.

#### DESCRIPTION OF THE PREFERRED EMBODIMENTS

5           The present invention will be described below with reference to the embodiment shown in the drawings.

Fig. 1 is a block diagram of an electronic still camera with a white balance control amount calculating device of a first embodiment of the present invention.

10           The electronic still camera is a single-lens reflex camera, and an interchangeable lens 11 is electrically connected to an electric circuit provided in the camera body through mount pins 12 and 13. A front lens group 14 and a rear lens group 15 are mounted in a lens barrel of the  
15 interchangeable lens 11, and an aperture 16 is provided between the lens groups 14 and 15. Each of the lens groups 14 and 15 is displaced in the optical axis direction under control of a lens control circuit 17, so that a focusing adjustment is carried out. The lens control circuit 17 is  
20 operated in accordance with a control signal transmitted through the mount pin 12 from a system controller 31 provided in the camera body. The aperture 16 is operated in accordance with a control signal transmitted through the mount pin 13 from an aperture drive circuit 32 provided in the camera body,  
25 so that the opening degree of the aperture 16 is adjusted.

The aperture drive circuit 32 is controlled by the system controller 31.

In the camera body, a quick return mirror 21 is disposed on the optical axis of the lens groups 14 and 15.

5 The quick return mirror 21 is rotatable between an inclined state shown in the drawing and a horizontal state in which the quick return mirror 21 is rotated upward. A focusing glass 22 is provided above the quick return mirror 21, and a pentagonal prism 23 is arranged above the focusing glass 22. An eyepiece  
10 lens 24 of a view-finder is disposed behind the pentagonal prism 23.

A shutter 25 is provided behind the quick return mirror 21, and an infrared cut filter 26 and an optical low-pass filter 27 are arranged behind the shutter 25. A CCD (i.e., an  
15 imaging device) is provided behind the optical low-pass filter 27. Namely, the quick return mirror 21, the shutter 25, the infrared cut filter 26 and the CCD 33 are aligned on the optical axis of the lens groups 14 and 15.

A rotating operation of the quick return mirror 21 is  
20 driven by a mirror drive circuit 34, and an open-close operation of the shutter 25 is driven by a shutter drive circuit 35. The mirror drive circuit 34 and the shutter drive circuit 35 are controlled by the system controller 31.

Usually, the mirror 21 is set to an inclined state, so  
25 that light passing through the interchangeable lens 11 is led







004720-0072950

photometry switch and a release switch. The photometry switch is turned ON by partly depressing the release button, so that a photometry is carried out by the photometry sensor 52. The release switch is turned ON by fully depressing the release button, so that the shutter 25 is open and closed. Namely, the CCD 33 is exposed, and thus an image signal corresponding to an image is generated in the CCD 33. The condition indicating device 55 is provided with a liquid crystal display, by which various setting conditions of the electronic still camera are indicated.

Fig. 2 is a block diagram showing a construction of the projection unit 53.

The projection unit 53 is provided with a light emitting diode 53a radiating an infrared laser beam and a projection lens 53b provided in front of the light emitting diode 53a. A light emitting operation of the light emitting diode 53a is controlled by a light emitting diode control circuit 53c, which is operated based on a command signal output by the system controller 31.

Fig. 3 is a view showing an external appearance of the interchangeable lens 11 and a focusing ring 61 attached to the interchangeable lens 11, the focusing ring 61 being disassembled from the interchangeable lens 11 in the drawing. The focusing ring 61 is rotatably provided on an outer surface of the lens barrel 62 of the interchangeable lens 11. The

03617100.071400  
focusing ring 61 is connected to a lens moving mechanism,  
which is mounted in the lens barrel 62 and is provided with a  
cam ring and the other components. By rotating the focusing  
ring 61, the lens groups 14 and 15 are moved in the optical  
5 axis direction so that a focusing adjustment is performed.

A two-dimensional bar code 63, indicating a distance  
from the camera to the subject, is provided on an inner  
surface of the focusing ring 61. A lens support cylinder (not  
shown), in which the lens groups 14 and 15 are housed, is  
10 disposed in the lens barrel 62. The lens support cylinder is  
fixed to the lens barrel 62, and a photo sensor 64 is attached  
on an outer surface of the lens support cylinder. The photo  
sensor 64 has a light emitting diode and a light receiving  
diode, and faces the two-dimensional bar code 63.

15 A light beam radiated from the light emitting diode is  
reflected on the two-dimensional bar code 63, and is received  
by the light receiving diode. The photo sensor 64 is  
connected to the lens control circuit 17 (Fig. 1), so that a  
signal, generated in the light receiving diode in accordance  
20 with received light, is input to the lens control circuit 17,  
and is then input to the system controller 31 provided in the  
camera body as a distance signal indicating a distance from  
the electronic still camera to the subject. Namely, the light  
radiated by the light emitting diode and reflected by the two-  
25 dimensional bar code is sensed by the light receiving diode,

the distance from the electronic still camera to the subject is measured.

Fig. 4 shows an example of an image P0 observed through the view-finder. The image P0 contains a subject P1 positioned close to the electronic still camera, a subject P2 positioned far from the electronic still camera, and a subject P3 positioned between the subjects P1 and P2. In this embodiment, as described later, only an image area containing the subject which is in-focus is extracted from the image, and a white balance adjustment is carried out based on an image signal regarding the image area. The image area is obtained by an operation in which, while the lens groups 14 and 15 focus on one of the subjects, distances from the camera to the subjects P1, P2 and P3 are measured and an image area corresponding to the distance signal obtained through the photo sensor 64 is detected.

With reference to Figs. 5 and 6, a principle behind a distance measurement in the embodiment is described below. Note, in Fig. 6, the abscissa indicates time "t".

A distance measuring light beam output by a distance measurement device B (corresponding to the projection unit 53 shown in Fig. 1) is reflected by a measurement subject P, and the reflected light beam is sensed by the CCD 33 (Fig. 1). The distance measuring light beam is a pulse, a width of which is "H". Accordingly, the reflected light beam is a pulse, a

width of which is "H", similarly to the distance measuring light beam. Therefore, a rise of the pulse of the reflected light beam occurs after a rise of the pulse of the distance measuring light beam by a time  $\delta \cdot t$  ( $\delta$  is a delay coefficient).

5 Since the distance measuring light beam and the reflected light beam have both traveled a distance "r" between the distance measurement device B and the measurement subject P, the distance "r" is represented as follows:

$$r = \delta \cdot t \cdot C / 2 \quad \dots (1)$$

10 wherein "C" is the velocity of light.

For example, by setting a condition in such a manner that the reflected light beam can only be sensed from a rise of the pulse of the distance measuring light beam to a point prior to a fall of the pulse of the reflected light beam, 15 i.e., by providing a gate pulse corresponding to a reflected light beam detecting period T, an amount "A" of received light from the reflected light beam becomes a function of the distance "r". Namely, the greater the distance "r" (or the greater the time  $\delta \cdot t$ ), the less the received light amount A.

20 In the embodiment, by taking advantage of the principle described above, the received light amount A is sensed using each of the photo-diodes (photoelectric conversion elements) of the CCD 28, the distance from the electronic still camera to each point on the surface of the measurement subject P is 25 sensed, and data of the three-dimensional image, which

indicates a topography of the measurement subject P, can be obtained concurrently.

Fig. 7 is a plan view showing a disposition of the photo-diodes 71 and a vertical transfer unit 72, which are provided in the CCD 33. Actually, a multitude of photo-diodes 71 are arranged in a matrix, and a corresponding vertical transfer unit 72 is disposed beside each vertical column of photo-diodes 71. Fig. 8 is a sectioned elevational view of the CCD 33 in which the CCD 33 is cut in a plane perpendicular to a substrate 73. The CCD 33 is an interline CCD of vertical overflow drain (VOD) type, in which unwanted charge is discharged to the substrate 73.

The photo-diodes 71 and the vertical transfer unit (signal charge holding unit) 72 are formed along a surface of the n-type substrate 73. A plurality of the photo-diodes 71 are two-dimensionally disposed in a matrix arrangement, and the vertical transfer unit 72 is disposed adjacent to the photo-diodes 71, parallel to rows extending in a vertical direction in Fig. 7. The vertical transfer unit 72 has four vertical transfer electrodes 72a, 72b, 72c and 72d, which correspond to each of the photo-diodes 71. Therefore, in the vertical transfer unit 72, four potential wells can be formed, so that a signal charge is output from the CCD 33 by controlling a depth of the wells, as is well-known. Note that a number of the vertical transfer electrodes can be changed,

depending upon a requirement of the CCD 33.

09617100-074100

The photo-diodes (PD) 71 and the vertical transfer unit (V-CCD, being a signal charge holding unit) 72 are disposed in a p-type well formed on a surface of the substrate 73. The p-type well is completely depleted due to an inverse-bias voltage applied between the p-type well and the n-type substrate 73. In this state, electric charge is accumulated in the photo-diodes 71, and an amount of the electric charge corresponds to an amount of an incident light beam, which is the reflected light beam reflected by the measurement subject. When a substrate voltage is changed to a value greater than a predetermined value, electric charge accumulated in the photo-diodes 71 is discharged to the substrate 73. Conversely, when an electric charge transfer signal, which is a voltage signal, is applied to a transfer gate (TG) 74, the electric charge accumulated in the photo-diodes 71 is transferred to the vertical transfer unit 72. Namely, after the electric charge is discharged to the substrate 73 by the electric charge discharging signal, the signal charge accumulated in the photo-diodes 71 is transferred to the vertical transfer unit 52 by the electric charge transfer signal. By repeating the discharge and the transfer, an electronic shuttering operation is performed.

Fig. 9 is a timing chart of a distance information sensing operation by which data, corresponding to the distance

from the electronic still camera to each point on a surface of the measurement subject, is sensed. The distance information sensing operation is described below with reference to Figs. 1, 7 through 9.

5 In synchronization with an output of a vertical synchronizing signal S1, an electric charge discharging signal (a pulse signal of negative polarity) S2 is output, so that unwanted charge, which is accumulated in the photo-diodes 71, is discharged to the substrate 73. Approximately  
10 simultaneously with a completion of the output of the electric charge discharging signal S2, the projection unit 53 is actuated, and thus a distance measuring light beam S3, which is a pulsed beam having a constant pulse-width, is output therefrom. The distance measuring light beam S3 is reflected  
15 by the measurement subject, and enters the CCD 33 as a reflected light beam S4. When a predetermined time has elapsed since the output of the distance measuring light beam S3, an electric charge transfer signal (a pulse signal of negative polarity) S5 is output, so that an electric charge  
20 accumulated in the photo-diodes 71 is transferred to the vertical transfer unit 72. Note that the electric charge transfer signal S5 is output before the output of a pulse of the distance measuring light beam S3 is completed.

Thus, for a period  $T_{u1}$  from the end of the output of the  
25 electric charge discharging signal S2 to the beginning of the

004720"0072650

output of the electric charge transfer signal S5, signal charge corresponding to distances from the electronic still camera to the measurement subject is accumulated in the photo-diodes 71. Namely, although a period  $T_s$ , which is from the fall of the pulse of the distance measuring light beam S3 to the rise thereof, and the electric charge accumulation period  $T_{u1}$  begin approximately simultaneously, the electric charge accumulation period  $T_{u1}$  ends prior to a completion of the period  $T_s$ , so that only a part of the reflected light beam S4 is detected by the CCD 33. Signal charge S6, generated due to the detected light beam, corresponds to the distance from the electronic still camera to the measurement subject. In other words, the signal charge S6, corresponding to a light beam, which is included in the reflected light beam S4 coming from the measurement subject and which reaches the photo-diodes 71 within the electric charge accumulation period  $T_{u1}$ , is accumulated in the photo-diodes 71. The signal charge S6 is transferred to the vertical transfer unit 72 by the electric charge transfer signal S5. Note that the period  $T_s$ , for which the distance measuring light beam S3 is output, can begin prior to the electric charge accumulation period  $T_{u1}$ , if necessary.

After a predetermined time has elapsed since the output of the electric charge transfer signal S5, the electric charge discharging signal S2 is again output, so that unwanted



charge, which is accumulated in the photo-diodes 71 after the transfer of the signal charge S6 to the vertical transfer unit 72, is discharged to the substrate 73. Thus, further signal charge is accumulated in the photo-diodes 71. Then, similarly  
5 to the above description, when the electric charge accumulation period  $T_{u1}$  has again elapsed, the signal charge S6 is transferred to the vertical transfer unit 72.

The transferring operation of the signal charge S6 to the vertical transfer unit 72 is repeatedly performed until  
10 the next vertical synchronizing signal S1 is output. Thus, the signal charge S6 is integrated in the vertical transfer unit 72. The signal charge S6 integrated for one field period, which is between two vertical synchronizing signals S1, corresponds to distance information of the measurement  
15 subject, on condition that the measurement subject is stationary for the period between the two vertical synchronizing signals S1.

The detecting operation of the signal charge S6 described above is carried out in all of the photo-diodes 71  
20 provided in the CCD 33. As a result of the detecting operation for one field period, the distance information sensed by the photo-diodes 71 is held in each corresponding vertical transfer unit 72, which is located adjacent to each column of photo-diodes 71. The distance information is output  
25 from the CCD 33 by a vertical transferring operation of the

vertical transfer units 72 and a horizontal transferring operation of a horizontal transfer unit (not shown). The distance information is then converted to digital data by the A/D convertor 38, and is stored in the memory 40 through the  
5 image signal processing circuit 39.

Figs. 10A and 10B show a flowchart of a routine by which an image area containing the in-focus subject is extracted and a white balance adjustment is performed based on an image signal corresponding to the image area. The routine  
10 is executed in the system controller 31 and is described with reference to Figs. 1, 3, 10A and 10B.

In Step 101, it is determined whether the photometry switch provided in the operation switch 54 is turned ON. When the photometry switch is turned ON, Step 102 is executed in  
15 which an exposure calculation is carried out based on a photometry value obtained by the photometry sensor 52. Namely, an aperture value and a shutter speed are obtained.

In Step 103, the lens groups 14 and 15 are moved along the optical axis, so that an automatic focusing (AF) operation  
20 is performed. The focusing condition is sensed by the AF sensor 51, and each of the lens groups 14 and 15 is set to a position where an in-focus condition is obtained, by an operation of the lens control circuit 17. The AF operation is carried out in such a manner that a subject positioned at the  
25 center, for example, of an image obtained through the lens

groups 14 and 15 is in-focus. In Step 104, a rotational position of the focusing ring 61, i.e. a distance from the electronic still camera to the in-focus subject is obtained based on a relative position of the photo sensor 64 to the two-dimensional bar code 63. A distance signal obtained through the photo sensor 64, i.e. in-focus distance data is stored in a memory (not shown) provided in the system controller 31.

In Step 105, it is determined whether the release switch provided in the operation switch 54 is turned ON. When the release switch is turned OFF, the process goes back to Step 101, so that the operations described above are again executed. Conversely, when the release switch is turned ON, Step 106 and the following Steps are executed.

In Step 106, an exposure operation is started. Namely, the quick return mirror 21 is rotated or set to a horizontal state, the opening degree of the aperture 16 is controlled to an amount corresponding to an aperture value set in Step 102, and the shutter 25 opens. In Step 107, it is determined whether an exposure period, which corresponds to a shutter speed obtained by the exposure calculation of Step 102, has elapsed. When the exposure period has elapsed, the process goes to Step 108, so that the exposure operation is stopped. Namely, the shutter 25 is closed, the quick return mirror 21 is set to an inclined state, and the aperture 16 is fully

opened.

In Step 109, an image signal, generated in the CCD 33 due to the exposure operation of Steps 106 through 108, is read. The image signal is converted to digital image data by the A/D convertor 38, and is then subjected to a predetermined process by the image signal processing circuit 39. The digital image data is stored in a first area of the memory 40. In Step 110, it is determined whether the reading operation of the image signal from the CCD 33 has been completed. When the reading operation has not been completed, Step 109 is repeatedly executed. Conversely, when the image signal corresponding to one frame image has been read from the CCD 33 and has been stored in the memory 40, the process goes from Step 110 to Step 111, so that an operation is carried out to sense three-dimensional image data indicating a distance from the electronic still camera to each point on the surface of the subject.

In Step 111, the exposure operation is again started. Namely, the quick return mirror 21 is again set to the horizontal state, and the opening degree of the aperture 16 is set to an amount for performing a sensing operation of the three-dimensional image data. Further, the shutter 25 opens. In Step 112, an electric power is supplied to the projection unit 53. In Step 113, controls of the projection unit 53 and the CCD 33 are started to perform a sensing operation of

three-dimensional image data. Namely, a pulse of a distance measuring light beam is output by the projection unit 53, a reflected light beam from the subject is received by the CCD 33, and a signal charge generated due to the reflected light beam is integrated in the CCD 33.

In Step 114, it is determined whether the sensing operation of the three-dimensional image data has been completed, i.e. whether the three-dimensional image data has been read from the CCD 33 and has been stored in a second area of the memory 40. When the storing operation of the three-dimensional image data has not been completed, Step 113 is repeatedly executed. When the storing operation of the three-dimensional image data has been completed, the process goes to Step 115, in which the exposure operation is stopped. Namely, the shutter 25 is closed, the quick return mirror 21 is set to an inclined state, and the aperture 16 is fully opened. Then, Step 116 is executed in which the projection unit 53 is extinguished.

In Step 117, based on the in-focus distance data obtained in Step 104 and the three-dimensional image data obtained in Step 113, one image area is extracted from the one frame image. For example, by selecting pixels, corresponding to points within a predetermined range from a distance indicated by the in-focus distance data which is deemed as the center, from the image data stored in the memory 40 in Step

109, the image area formed by the selected pixels is obtained. The image area corresponds to an image which contains subjects located at approximately the same distance as the subject P1, when only the subject P1 is in-focus in the example shown in Fig. 4.

In Step 118, a part in which a value of color differential data, obtained based on the image data contained in the image area extracted in Step 117, is within a predetermined range, i.e., an achromatic image is extracted.

10 In Step 119, an average value of color differential data corresponding only to the achromatic image obtained in Step 118 is obtained, and is stored in the memory 40 as a control amount for a white balance adjustment. In Step 120, using the control amount obtained in Step 119, the white balance  
15 adjustment is applied to the image data which is stored in the memory 40 in Step 109. Since the white balance adjustment is well known, an explanation thereof is omitted.

As described above, in the first embodiment, only an image area is extracted which is formed by image data  
20 corresponding to a subject located at approximately the same distance as the in-focus subject. Then, an achromatic image is extracted from the image of the extracted image area, and the control amount of the white balance adjustment is calculated based on only the achromatic image. Therefore, the  
25 white balance adjustment is always performed with regard to

the in-focus subject, so that an appropriate color expression can be always obtained for the subject.

Figs. 11A and 11B show a flowchart of a white balance adjustment routine of a second embodiment. The other  
5 constructions are the same as the first embodiment.

When it is confirmed in Step 201 that the photometry switch is turned ON, Step 202 is executed in which an exposure calculation is carried out based on a photometry value obtained by the photometry sensor 52, so that an aperture  
10 value and a shutter speed are obtained. In Step 203, the lens groups 14 and 15 are moved along the optical axis, so that an AF operation is performed so that the lens groups 14 and 15 are set to predetermined positions. In Step 205, it is determined whether the release switch is turned ON. When the  
15 release switch is turned OFF, the process goes back to Step 201, and when the release switch is turned ON, Steps 206 and the following Steps are executed.

Operations of Steps 206 through 216 are identical to those of Steps 106 through 116.

20 In Step 217, based on the three-dimensional image data obtained in Step 213, a single image, corresponding to image data obtained in Step 209, is divided into three image areas, for example. Namely, as shown in Fig. 4, for example, a single image P0 is divided into a first image area P10  
25 composed of a subject P1 of a short distance, a second image

area P20 composed of a subject P2 of a long distance, and a third image area P30 composed of a subject P3 of an intermediate distance. Note that, although, in Fig. 4, outlines of the image areas P10, P20 and P30 are shown as rectangular similarly to the original image P0, actually, each of the image areas P10, P20 and P30 is divided by clear boundary lines, which are usually not rectangular. The division of the image areas will be described later.

In Step 218, image data of the first image area P10 is extracted. In Step 219, a part in which a value of color differential data, obtained based on the image data contained in the image area extracted in Step 218, is within a predetermined range, i.e., an achromatic image is extracted. In Step 220, an average value of color differential data corresponding only to the achromatic image obtained in Step 219 is obtained, and a white balance adjustment of the corresponding image area is performed using the average value as a correction amount of the white balance adjustment.

In Step 221, it is determined whether the white balance adjustment has been completed for all of the first, second and third image areas. When the white balance adjustment has not been completed for all of the image areas, Step 222 is executed, in which image data of the next image area is extracted. Then, Steps 219 and 220 are again executed, and the white balance adjustment is carried out for the image



area. When it is determined in Step 221 that the white balance adjustment has been completed, the white balance adjustment routine ends.

With reference to Fig. 12, the division of the image areas executed in Step 217 of Fig. 11B is described. Fig. 12 is a histogram, in which a reciprocal number of a distance "d" from the electronic still camera to the subject is defined as the abscissa and a number of pixels corresponding to the distance is defined as the ordinate.

10 A histogram of distance information is made regarding all of the pixels forming the three-dimensional image data obtained in Step 213. Since pixels of infinity are contained in the photographed image, if a distance is defined as the abscissa of the histogram, the abscissa of the histogram would  
15 be extended to infinity. Further, the minimum distance at which a photographing operation can be performed, is finite. Therefore, a reciprocal number of the distance "d" is defined as the abscissa, and the maximum value of the abscissa is set to a finite value.

20 As shown in Fig. 4, when three subjects P1, P2 and P3, in which distances from the electronic still camera are different, are included in a single image, three peaks including infinity, i.e. a point of  $1/d=0$  exist in the histogram. Namely, the subject P2 is located at infinity, and  
25 the second image area P20 containing the subject P2

corresponds to the left peak PK0 of the histogram. The subject P3 is located at an intermediate distance, and the third image area P30 containing the subject P3 corresponds to the center peak PK1 of the histogram. The subject P1 is located at a short distance, and the first image area P10 containing the subject P1 corresponds to the right peak PK2 of the histogram.

A minimal point, which is positioned at the equal distance from the adjacent peaks PK0 and PK1, is defined as a first boundary V1, and a minimal point, which is positioned at the equal distance from the adjacent peaks PK1 and PK2, is defined as a second boundary V2. In Fig. 4, the second image area P20 corresponds to a histogram positioned at a left side of the first boundary V1, and the third image area P30 corresponds to a histogram positioned between the first and second boundaries V1 and V2. The first image area P10 corresponds to a histogram positioned at a right side of the second boundary V2.

As described above, in the second embodiment, a single image is divided into a plurality of image areas in accordance with a distance from the electronic still camera to the subjects, and for each of the image areas, a white balance adjustment is performed using image data of an achromatic part of the image area. Therefore, the white balance adjustment is properly performed for the image as a whole.

Although the embodiments of the present invention have been described herein with reference to the accompanying drawings, obviously many modifications and changes may be made by those skilled in this art without departing from the scope  
5 of the invention.

The present disclosure relates to subject matter contained in Japanese Patent Application No. 11-201136 (filed on July 15, 1999) which is expressly incorporated herein, by reference, in its entirety.

1. Introduction  
 2. Background  
 3. Methodology  
 4. Results  
 5. Discussion  
 6. Conclusion  
 7. References  
 8. Appendix  
 9. Index  
 10. Table of Contents  
 11. Figure  
 12. Table  
 13. Figure  
 14. Table  
 15. Figure  
 16. Table  
 17. Figure  
 18. Table  
 19. Figure  
 20. Table  
 21. Figure  
 22. Table  
 23. Figure  
 24. Table  
 25. Figure  
 26. Table  
 27. Figure  
 28. Table  
 29. Figure  
 30. Table  
 31. Figure  
 32. Table  
 33. Figure  
 34. Table  
 35. Figure  
 36. Table  
 37. Figure  
 38. Table  
 39. Figure  
 40. Table  
 41. Figure  
 42. Table  
 43. Figure  
 44. Table  
 45. Figure  
 46. Table  
 47. Figure  
 48. Table  
 49. Figure  
 50. Table  
 51. Figure  
 52. Table  
 53. Figure  
 54. Table  
 55. Figure  
 56. Table  
 57. Figure  
 58. Table  
 59. Figure  
 60. Table  
 61. Figure  
 62. Table  
 63. Figure  
 64. Table  
 65. Figure  
 66. Table  
 67. Figure  
 68. Table  
 69. Figure  
 70. Table  
 71. Figure  
 72. Table  
 73. Figure  
 74. Table  
 75. Figure  
 76. Table  
 77. Figure  
 78. Table  
 79. Figure  
 80. Table  
 81. Figure  
 82. Table  
 83. Figure  
 84. Table  
 85. Figure  
 86. Table  
 87. Figure  
 88. Table  
 89. Figure  
 90. Table  
 91. Figure  
 92. Table  
 93. Figure  
 94. Table  
 95. Figure  
 96. Table  
 97. Figure  
 98. Table  
 99. Figure  
 100. Table  
 101. Figure  
 102. Table  
 103. Figure  
 104. Table  
 105. Figure  
 106. Table  
 107. Figure  
 108. Table  
 109. Figure  
 110. Table  
 111. Figure  
 112. Table  
 113. Figure  
 114. Table  
 115. Figure  
 116. Table  
 117. Figure  
 118. Table  
 119. Figure  
 120. Table  
 121. Figure  
 122. Table  
 123. Figure  
 124. Table  
 125. Figure  
 126. Table  
 127. Figure  
 128. Table  
 129. Figure  
 130. Table  
 131. Figure  
 132. Table  
 133. Figure  
 134. Table  
 135. Figure  
 136. Table  
 137. Figure  
 138. Table  
 139. Figure  
 140. Table  
 141. Figure  
 142. Table  
 143. Figure  
 144. Table  
 145. Figure  
 146. Table  
 147. Figure  
 148. Table  
 149. Figure  
 150. Table  
 151. Figure  
 152. Table  
 153. Figure  
 154. Table  
 155. Figure  
 156. Table  
 157. Figure  
 158. Table  
 159. Figure  
 160. Table  
 161. Figure  
 162. Table  
 163. Figure  
 164. Table  
 165. Figure  
 166. Table  
 167. Figure  
 168. Table  
 169. Figure  
 170. Table  
 171. Figure  
 172. Table  
 173. Figure  
 174. Table  
 175. Figure  
 176. Table  
 177. Figure  
 178. Table  
 179. Figure  
 180. Table  
 181. Figure  
 182. Table  
 183. Figure  
 184. Table  
 185. Figure  
 186. Table  
 187. Figure  
 188. Table  
 189. Figure  
 190. Table  
 191. Figure  
 192. Table  
 193. Figure  
 194. Table  
 195. Figure  
 196. Table  
 197. Figure  
 198. Table  
 199. Figure  
 200. Table  
 201. Figure  
 202. Table  
 203. Figure  
 204. Table  
 205. Figure  
 206. Table  
 207. Figure  
 208. Table  
 209. Figure  
 210. Table  
 211. Figure  
 212. Table  
 213. Figure  
 214. Table  
 215. Figure  
 216. Table  
 217. Figure  
 218. Table  
 219. Figure  
 220. Table  
 221. Figure  
 222. Table  
 223. Figure  
 224. Table  
 225. Figure  
 226. Table  
 227. Figure  
 228. Table  
 229. Figure  
 230. Table  
 231. Figure  
 232. Table  
 233. Figure  
 234. Table  
 235. Figure  
 236. Table  
 237. Figure  
 238. Table  
 239. Figure  
 240. Table  
 241. Figure  
 242. Table  
 243. Figure  
 244. Table  
 245. Figure  
 246. Table  
 247. Figure  
 248. Table  
 249. Figure  
 250. Table  
 251. Figure  
 252. Table  
 253. Figure  
 254. Table  
 255. Figure  
 256. Table  
 257. Figure  
 258. Table  
 259. Figure  
 260. Table  
 261. Figure  
 262. Table  
 263